

## Таблица скорости записи

### 4-канальный регистратор RMH-0428EU-1

АHD камеры+ IP камеры	1 Мр АHD (fps)	2 Мр АHD (fps)	4 Мр АHD (fps)	5 Мр АHD (fps)	IPC 1-5 Мр(fps)
4---	25	12	7	6	25-30
3+1	25	16	10	8	25-30
2+2	25	25	15	12	25-30
1+3	25	25	15	12	25-30

### 8-канальный регистратор RMH-0828EU-1

АHD камеры+ IP камеры	1 Мр АHD (fps)	2 Мр АHD (fps)	4 Мр АHD (fps)	5 Мр АHD (fps)	IPC 1-5 Мр(fps)
8---	25	12	7	6	25-30
7+1	25	14	8	6	25-30
6+2	25	16	10	8	25-30
5+3	25	20	12	9	25-30
4+4	25	25	15	12	25-30
3+5	25	25	15	12	25-30
2+6	25	25	15	12	25-30
1+7	25	25	15	12	25-30

### 16-канальный регистратор RMH-1628MU-4

АHD камеры+ IP камеры	1 Мр АHD (fps)	2 Мр АHD (fps)	4 Мр АHD (fps)	5 Мр АHD (fps)	IPC 1-5 Мр(fps)
16---	25	12	7	6	25-30
15+1	25	13	8	6	25-30
14+2	25	14	8	6	25-30
13+3	25	15	9	8	25-30
12+4	25	15	10	8	25-30
11+5	25	18	10	9	25-30
10+6	25	20	12	9	25-30
9+7	25	22	13	9	25-30
8+8	25	25	13	9	25-30
7+9	25	25	15	12	25-30
6+10	25	25	15	12	25-30
5+11	25	25	15	12	25-30
4+12	25	25	15	12	25-30
3+13	25	25	15	12	25-30
2+14	25	25	15	12	25-30
1+15	25	25	15	12	25-30